

ACER Grinders Power Consumption

	Supra 618II		Supra 618AHII		AGS 1020AHD		AGS 1224AHD		AGS 1632AHD		AGS 2040/60AHD		AGS 2448AHD	
230V/460V	230	460	230	460	230	460	230	460	230	460	230	460	230	460
Spindle Motor (HP)	3HP	3HP	3HP	3HP	2HP	2HP	5HP	5HP	7.5HP	7.5HP	10HP	10HP	15HP	15HP
(AMP)	12	6	12	6	8	4	20	10	30	15	40	20	60	30
Hydraulic Motor (HP)	N/A	N/A	1	1	2	2	2	2	3	3	5	5	7.5	7.5
(AMP)	N/A	N/A	4	2	8	4	8	4	12	6	20	10	30	15
Auto Crossfeed (HP)	N/A	N/A	0.5	0.5	0.2	0.2	0.2	0.2	0.2	0.2	0.25	0.25	0.25	0.25
(AMP)	N/A	N/A	2	1	0.8	0.4	0.4	0.8	0.8	0.4	1	0.5	1	0.5
Total (HP)	3HP	3HP	4.5HP	4.5HP	4.2HP	4.2HP	7.2HP	7.2HP	10.7HP	10.7HP	15.25HP	15.25HP	22.75	22.75
(AMP)	12	6	18	9	16.8	8.4	28.4	14.8	42.8	21.4	61	30.5	91	45.5